

شركة غاز الجنوب

الهيئة الفنية

شعبة السيطرة الفنية

محطة كهرباء معمل الغاز السائل

ت	الفقرة	الوحدة	الكمية	السعر	المبلغ
١	<p>المواد الكهربائية :- وتشمل التجهيز والنصب والتأسيس وكما يلي :-</p> <p>١- بزل كهرباء للجهد العالي (33kv) كامل التسليك والتوصيلات الداخلية ومزود بأجهزة حماية كاملة ودوائر سيطرة للتشغيل والإطفاء اليدوي والتلقائي {الأوتوماتيكي} مع كافة الملحقات accessories من أجهزة الفحص ومستلزمات الصيانة من أدوات وعدد لأعمال الصيانة النصب والرفع وغيرها على أن تزود بشهادات المنشأ مصدقة من السفارة العراقية في بلد المنشأ وفي حالة عدم القدرة على تجهيز من الشركة الأصلية يهمل العطاء ويحتوي بزل الضغط العالي (33KV) على ما يلي :-</p> <p>A-One Main Incomer consist of :</p> <p>1-SF6 C.B,33KV,1250A,25KA,Drawable,type Air Insulated (AIS),Motorized</p> <p>2-Earthing switch.</p> <p>3-Set of C.Ts .</p> <p>4-Set of P.Ts .Withdrawble Fuse .</p> <p>5-Digital protection relay Sepam or Micom included the protections(phase overcurrent ,instantaneous current, over and under voltage and other necessary protections)</p> <p>B-Three transformer feeder ,each of feeder consists of :</p> <p>1-SF6 C.B,33KV,630A,25KA,Drawable,type Air Insulated (AIS),Motorized</p> <p>2-Earthing switch.</p> <p>3-Set of C.Ts .</p> <p>4-Set of P.Ts .</p> <p>5-Digital protection relay Sepam or Micom included the protections(phase overcurrent ,instantaneous current, over and under voltage and other necessary protections).</p> <p>Origin :Schneider Electric (France),Siemense(Germany),Areva(France)</p>	سيت	١		